

Audio Installation Guide

Audio Cables:

(2 Beige cables-one with Pink end, one with Green)

Since the audio connection on the motherboard is not standardized yet, to avoid any confusion, so please check with your Motherboard menu for installation.

PIN	BCC Case Headers	AC'97 Audio MB	HD Audio MB	Asus MB
1	MIC-In	MIC	PORT 1L	MIC2
2	GROUND	AUD_GND	GND	AGND
3	MIC-BIAS	MIC_BIAS	PORT 1R	MICPWR
4				
5	SPEAKER-R	FP_OUT_R	PORT 2R	LINE OUT_R
6	RETURN-R	FP_RETURN_R	SENSE1_RETURN	BLINE_OUT_R
7			SENSE_SEND	
8				
9	SPEAKER-L	FP_OUT_L	PORT 2L	LINE OUT_L
10	RETURN-L	FP_RETURN_L	SENSE2_RETURN	BLINE_OUT_L

Note: Above shown are PIN connections for AC'97 Audio & Intel® HD Audio Standard
MB Manufacturers may have different names for the connectors but the PIN layout is standard.